



MSD PART NUMBER	HP	VOLTAGE	CURRENT	WEIGHT	TERMINAL BLOCK	GROUND LUG
MSD0008C300	5	600V	8 AMPS	57LBS	WIRE RANGE: 1-22AWG	WIRE RANGE: 1/0 -14AWG
MSD0010C300	7.5	600V	10 AMPS	58LBS	WIRE RANGE: 1-22AWG	WIRE RANGE: 1/0 -14AWG
MSD0012C300	10	600V	12 AMPS	58LBS	WIRE RANGE: 1-22AWG	WIRE RANGE: 1/0 -14AWG

NOTE: FOR WIRE RANGE AND TORQUE INFORMATION SEE IOM MANUAL.

CUSTOMER IS RESPONSIBLE FOR INSTALLATION TO MEET ALL NATIONAL AND LOCAL ELECTRICAL CODES.

				TOLERANCES (EXCEPT AS NOTED)		TOL		W132 N10611 Grant Drive Germantown, WI 53022	
				DECIMAL		.XX +/- .25		MSD 8 AMPS TO 12 AMPS MotorShield Sinewave Filter 600/3/60, Type 1/ 3R.	
				FRACTIONAL		+/- 1/16		DRN. BY BWM	
				ANGULAR		+/- 1		DATE 12/28/15	
								SCALE 1/3	
								APRVD.	
								DWG. No. 105801DG	
								SHEET 1 OF 1	
B	3696 ADD DISCHARGE LABEL	7/29/16	DSW						
A	AS BUILT	12/28/15	BWM						
NO	REVISION	DATE	BY						